

Create / Update a Location

Overview

Create or update a location from the location finder. If you just need to remove a location, without replacing it, you should use the [Delete a Location](#) step-by-step.

Pre-requisite: This guide considers that the concerned location map is in place. For details about that, see the [Manage Locations](#) page.

Advanced level

This operation needs to use the "Tridion Content Manager" instead of the better known "Site Edit".

Table of contents

- [Overview](#)
- [Table of contents](#)
- [Step-by-step](#)
 - [Step 1 : Create or update a location](#)
 - [a. Create a location](#)
 - [b. Update a location](#)
 - [Step 2: Publish new / updated location](#)
- [Related articles](#)
- [Can't find information?](#)

Step-by-step

Step 1 : Create or update a location


1. According to your entity, go to the following location in the Tridion Content Manager:
SW C1 Master-en \ Building blocks \ Component \ 1 ONE \ ... \ [Your entity folder] \ Locations

Creation / Update are is a "C1 Master-XX" publication

The 1st container of this path ("C1 Master-en") is named a "Publication". For the Step 2 ("Publish a location"), the publication to use it not the same than here for creating / updating.

Not in Solvay ONE?

If the concerned web site is not Solvay ONE, you should be able to adapt the path by yourself (e.g. "1 Internet Webfactory" instead of "1 ONE").




a. Create a location

Advanced level

This option is valid only when you need to create an additional location not updating one.

1. On Create tab, click on New Component. A form opens.



2. Fill in the name

3. Fill-in the title (corresponding to your location title)

4. You can include a short description related to the location (not mandatory)

The screenshot shows the 'New Component' form in the SDL Tridion interface. The breadcrumb trail at the top is 'SW C1 Master-en > Building Blocks > Component > 1 ONE > GBU > Peroxides > 3 Locations'. The form has several tabs: 'General', 'Metadata', 'Source', 'Workflow', 'Comments', 'Ratings', and 'Info'. The 'General' tab is selected. It contains a field for '* Name:' with the value 'New Component'. Below this is a section for 'Component Content' with a field for '* Title:'. There is also a 'Short description:' section with tabs for 'Design', 'Source', and 'Preview'. The 'Design' tab is selected, showing a large text area for the description.

5. Enter the address. To include several rows, click on the + icon

6. Select the country in the list

The screenshot shows the 'Address' and 'Country' fields in the SDL Tridion interface. The 'Address' field is labeled '* Address:' and has a text input area with a '+' icon to add multiple rows. Below it is the 'Country' field, labeled '* Country:', which has a dropdown menu showing a list of countries: Argentina, Australia, Austria, Belgium, and Brazil.

7. Fill-in the entity information. To include several entities, click on the + icon.

The screenshot shows the 'Entity information' form in the SDL Tridion interface. It has a section titled 'Entity information:' with a '+' icon to add multiple entities. The form contains several fields: '* Entity:' (text input), '* Role:' (dropdown menu with options: Headquarter, Office, Production Site, Research Center), 'Phone:' (text input), 'Fax:' (text input), and 'Email:' (text input).

8. Enter the longitude & latitude for the location.

9. Select a GBU if relevant

10. Tag your location with your entity tag.

* Longitude:

* Latitude:


GBU:

Acetow
Aroma Performance
Chlor Chemicals
Coatis
Composite Materials
Emerging Biochemicals
Energy Services
Engineering Plastics
Fibras
Novecare
Performance Polyamides
Peroxides
Polyamide & Intermediates
Rare Earth Systems
Silica
Soda Ash & Derivatives
Solvin
Special Chem
Specialty Polymers
Technology Solutions

Tags:




11. Save & Close your component to save your new location



b. Update a location

2. Select the location to modify & double click on it to open the form.




3. In the form, update all elements that have changed (see a.create a location)

The screenshot shows the SAP location management form for 'Solvay Buenos Aires'. The breadcrumb trail is 'SW C1 Master-en > Building Blocks > Component > 1 ONE > GBU > Costs > 3 Locations'. The 'General' tab is active, showing the following fields:

- Name:** Solvay Buenos Aires
- Component Content:**
 - Title:** Solvay Argentina
 - Short description:** (empty)
- Address:**
 - AVENIDA ALICIA MOREAU DE JUSTO 1930
 - 4 PISO - PUERTO MADERO
 - C1107AFN BUENOS AIRES
- Country:** Argentina (selected from a dropdown list including Australia, Austria, Belgium, and Brazil)
- Entity information:**
 - Entity:** SOUTH CONE (Argentina, Chile and Uruguay)
 - Role:** Headquarter (selected from a dropdown list including Office, Production Site, and Research Center)

4. Click on Save & Close to save your updated contact.



Step 2: Publish new / updated location

1. According to your entity, go to the following location in the Tridion Content Manager:
SW W1 ONE-Master \ Building blocks \ Component \ 1 ONE \ ... \ [Your entity folder] \ Locations



Creation / Update are in a "C1 Master-XX" publication


The folders are the same than on Step 1, but here you had to switch from the "SW C1 Master" publication to the "SW W1 ONE-Master" one.



Not in Solvay ONE?

If the concerned web site is not Solvay ONE, you should be able to adapt the path by yourself (e.g. "SW W2 Webfactory Proban-en" instead of "SW W1 ONE-Master").


2. Select the location to publish



3. Click on Publish icon. A pop-in opens.

4. Stick Staging &/or Live to publish the location. Click on advanced to stick "Also publish in child publications".

Your new / updated location will appear on your location map page.



Related articles

[Manage Locations](#)

[Create / Update a Location](#)

Can't find information?

- [Web support contact](#)